

Spectrum Compact 56-71 GHz

JOSSAP61 datasheet



Measurements

- Channel Power (measures the total power in a specified bandwidth)
- Adjacent channel power
- Signal bandwidth
- Center frequency
- Interference detection
- Mask

Setup Parameters

- Frequency: Center/Start/Stop
- Trace mode: Normal, Max hold, Cumulative, # of Averages
- Span: Max Span, Min Span, Selected Span

Save

- Proprietary format
- Saves actual data
- Continuous sweep record

Sweep Functions

- Sweep: Continuous, Manual Trigger

SAF Spectrum Compact 56-71 GHz datasheet

Product features may vary between different models and configurations. They are subject to change without prior notice.

Spectrum Compact 56-71 GHz

JOSSAP61 datasheet



Trace Functions

- Trace operations: Normal, Max hold, # of Averages, Cumulative

Marker Functions

- Marker: Peak search, set marker to center

Settings

- Detector MIN, AVG, MAX
- Signal ID

Remote control

- Spectrum Manager PC software
- API commands

Frequency <ul style="list-style-type: none">▪ Frequency Range 56 000 – 71 000 MHz▪ Frequency Resolution 10 MHz▪ Frequency Reference Aging ± 1.0 ppm/1 year Accuracy: ± 2.5 ppm ($25^{\circ}\text{C} \pm 25^{\circ}\text{C}$) + aging▪ Frequency span 1000 MHz to full		
Bandwidth (Performance Sweep Mode) <ul style="list-style-type: none">▪ RBW 10 MHz▪ VBW 300 kHz;		
Amplitude Ranges <ul style="list-style-type: none">▪ Measurement Range DANL to -40 dBm Amplitude Accuracy (single sine wave input, Performance Sweep Mode) 20° C to 30° C Typical: ± 1 dB		
VSWR 56 000 – 67 000 MHz ≤ 2.0 typ.		
SSB Phase Noise on RF input		
Carrier offset	20°C to 30°C 100 kHz offset	≤ -80 dBc/Hz
Maximum Input Level		
DC voltage	0 V	
CW RF power	-40 dBm (0.0001 mW),	
Max. Damage level	0 dBm (1mW)	
Displayed Average Noise Level (DANL) AVG detector, trace average 16, 20°C to 30°C, input impedance = 50 Ω -90 dBm* @ RWB = 10 MHz * Guaranteed for Frequency Range 56 000 – 67 000 MHz		

SAF Spectrum Compact 56-71 GHz datasheet

Product features may vary between different models and configurations. They are subject to change without prior notice.

Spectrum Compact 56-71 GHz

J0SSAP61 datasheet



Level Display	
Trace detectors	AVG; MAX; MIN
Trace functions	Clear write, max hold, average, cumulative, min/max hold
Frequency response	
56 000 – 71 000MHz; amplitude accuracy ± 1 dBm	
RF Input Connector	
Impedance	50 Ω (nom.)
Connector	Waveguide flange UG385/U
Sweep	
Sweep time	
MIN SPAN=1000 MHz	MIN SPAN = 500 ms
Display	
Type	TFT LCD resistive touchscreen
Resolution	480 x 272
Size	4.3 inch (Diagonal)
Active area	95 x 53.8 mm
Mass memory	
8 GB	
Input voltage	
USB micro: 5V DC 1.5A	
DC input: 5.9V DC 3A	
Interface USB micro	
Battery life up to 3h	
Operating temperature -15°C to +55°C / 5°F to 131°F	
Dimensions 147 x 83 x 34 mm / 5.79 x 3.27 x 1.34 inch	
Weight 0.57 kg / 20.11 oz	

For more detailed information about SAF products visit www.saftehnika.com or contact your SAF representative info@saftehnika.com. Product features may vary between different models and configurations. They are subject to change without prior notice.

SAF Tehnika © 2021

SAF Spectrum Compact 56-71 GHz datasheet

Product features may vary between different models and configurations. They are subject to change without prior notice.